


PRODUCT-DETAILS

EF96-100

EF96-100 Electronic Overload Relay 36 ... 100 A



General Information

| | |
|-----------------------|---|
| Extended Product Type | EF96-100 |
| Product ID | 1SAX341001R1101 |
| EAN | 4013614442247 |
| Catalog Description | EF96-100 Electronic Overload Relay 36 ... 100 A |

| | |
|------------------|---|
| Long Description | <p>The EF96 is a self-supplied electronic overload relay, which means no extra external supply is needed. It offers reliable and fast protection for motors in the event of overload or phase failure. Easy to use like a thermal overload relay and compatible with standard motor applications, the electronic overload relay is convincing, above all, due to its wide setting range, high accuracy, high operational temperature range and the possibility to select a trip class (10E, 20E, 30E). Further features are the temperature compensation, trip contact (NC), signal contact (NO), automatic- or manual reset selectable, trip-free mechanism, STOP- and Test function and a trip indication. The overload relays are connected directly to the contactors. Single mounting kits are available as accessory. The EF65, EF96 and EF146 have ATEX and IECEx certification 1)</p> |
|------------------|---|

1) ATEX is valid for products produced from week 42, 2014.
IECEx is valid for products produced from week 15, 2017.

Ordering

| | |
|------------------------|----------|
| Minimum Order Quantity | 1 piece |
| Customs Tariff Number | 85364900 |

| Popular Downloads | |
|-----------------------------------|------------------------------------|
| Data Sheet, Technical Information | 2CDC107041D0201 |
| Instructions and Manuals | 2CDC107027M6803 |
| Instructions and Manuals (Part 2) | 1SAC200017M0002 |
| Ex Operating Instructions | 2CDC107043M6801 |
| Time-Current Characteristic Curve | 1SAX100509F0002 1SAX100510F0001 |
| CAD Dimensional Drawing | 2CDC001079B0201 |
| Dimension Diagram | 1SAX300406F0001 |

| Dimensions | |
|----------------------------|----------|
| Product Net Width | 70 mm |
| Product Net Height | 132.7 mm |
| Product Net Depth / Length | 105.2 mm |
| Product Net Weight | 0.802 kg |

| Technical | |
|--|--|
| Setting Range | 36 ... 100 A |
| Rated Operational Voltage | Auxiliary Circuit 600 V AC/DC Main Circuit 1000 V AC |
| Rated Operational Current (I _e) | 100 A |
| Rated Frequency (f) | Auxiliary Circuit 50 Hz Auxiliary Circuit 60 Hz Auxiliary Circuit DC Main Circuit 50 Hz Main Circuit 60 Hz |
| Rated Impulse Withstand Voltage (U _{imp}) | Auxiliary Circuit 6 kV Main Circuit 8 kV |
| Rated Insulation Voltage (U _i) | 1000 V |
| Number of Poles | 3 |
| Number of Auxiliary Contacts NC | 1 |
| Number of Auxiliary Contacts NO | 1 |
| Number of Protected Poles | 3 |
| Conventional Free-air Thermal Current (I _{th}) | Auxiliary Circuit NC 6 A Auxiliary Circuit NO 6 A |
| Rated Operational Current AC-15 (I _e) | (240 V) NC 3 A (240 V) NO 3 A (400 V) NC 1.1 A (400 V) NO 1.1 A (500 V) NC 0.75 A (500 V) NO 0.75 A |
| Rated Operational Current DC-13 (I _e) | (125 V) NC 0.55 A (125 V) NO 0.5 A (24 V) NC 1.5 A (24 V) NO 1.5 A |

| | |
|--|--|
| | (250 V) NC 0.27 A (250 V) NO 0.27 A (60 V) NC 0.55 A (60 V) NO 0.55 A |
| Degree of Protection | Housing IP20 Main Circuit Terminals IP10 |
| Pollution Degree | 3 |
| Connecting Capacity Auxiliary Circuit | Flexible with Ferrule 1/2x 0.75 ... 2.5 mm ² Flexible with Insulated Ferrule 1/2x 0.75 ... 2.5 mm ² Flexible 1/2x 0.75 ... 2.5 mm ² Rigid 1/2x 1 ... 4 mm ² |
| Connecting Capacity Main Circuit | Flexible with Ferrule 2x 4 ... 35 mm ² Flexible with Ferrule 1x 4 ... 50 mm ² Flexible with Insulated Ferrule 2x 2 ... 35 mm ² Flexible with Insulated Ferrule 1x 4 ... 50 mm ² Flexible 1x 4 ... 50 mm ² Flexible 2x 4 ... 35 mm ² Rigid 1x 4 ... 70 mm ² Rigid 2x 4 ... 35 mm ² |
| Tightening Torque | Auxiliary Circuit 0.8 ... 1.2 N·m Main Circuit 6 N·m |
| Wire Stripping Length | Auxiliary Circuit 9 mm Main Circuit 20 mm |
| Recommended Screw Driver | Auxiliary Circuit Pozidriv 2 Main Circuit Hexagon 4 |
| Mounting Position | 1 ... 6 |
| Power Loss | at Rated Operating Conditions per Pole 0.117 ... 0.9 W |
| Suitable For | AF80 AF96 |
| Standards | IEC/EN 60947-1 IEC/EN 60947-4-1 IEC/EN 60947-5-1 UL 60947-1 UL 60947-4-1 |

Technical UL/CSA

| | |
|---|--|
| Maximum Operating Voltage UL/CSA | Main Circuit 600 V AC |
| Contact Rating UL/CSA | (NC:) B600 (NC:) Q600 (NO:) B600 (NO:) Q600 |
| Connecting Capacity Main Circuit UL/CSA | Flexible 1/2x 10-2 AWG Stranded 1/2x 10-2 AWG |
| Connecting Capacity Auxiliary Circuit UL/CSA | Flexible 1/2x 18-10 AWG Stranded 1/2x 18-10 AWG |
| Tightening Torque UL/CSA | Auxiliary Circuit 7 ... 1 in·lb Main Circuit 70 in·lb |

Environmental

| | |
|---|--|
| Ambient Air Temperature | Operation -25 ... +70 °C Operation Compensated -25 ... +70 °C Storage -50 ... +85 °C |
| Ambient Air Temperature Compensation | Yes |
| Maximum Operating Altitude Permissible | 2000 m |
| Resistance to Shock acc. to IEC 60068-2-27 | 11 ms Pulse 25g |

Resistance to Vibrations 5g 3 ... 150 Hz

RoHS Status Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

Material Compliance

| | |
|---|--|
| Conflict Minerals Reporting Template (CMRT) | 9AKK108467A5658 |
| REACH Declaration | No declaration needed |
| RoHS Information | 2CMT2021-006277 |
| RoHS Status | Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019 |
| WEEE B2C / B2B | Business To Business |
| WEEE Category | 5. Small Equipment (No External Dimension More Than 50 cm) |

Circular Value

| | |
|--------------------------|-----------------|
| ABB EcoSolutions | Yes |
| End of Life Instructions | 1SAC200283H0001 |

Eco Transparency

| | |
|---------------------------|-----------------|
| Environmental Information | 1SAC200099H0001 |
|---------------------------|-----------------|

Certificates and Declarations

| | |
|----------------------------------|---------------------|
| ABS Certificate | 1SAA941002-0102 |
| ATEX Certificate | 1SAA941004-3901 |
| BV Certificate | 1SAA941002-0201 |
| CB Certificate | 1SAA964013-2001 |
| CCS Certificate | 1SAA941001-0901 |
| CQC Certificate | CQC2013010309592132 |
| Declaration of Conformity - CCC | 2020980309000286 |
| Declaration of Conformity - CE | 1SAD101100-3601 |
| Declaration of Conformity - UKCA | 1SAD201100-3601 |
| DNV Certificate | 1SAA941003-0302 |
| EAC Certificate | 1SAA941003-2701 |
| IECEX Certificate | 1SAA941000-4001 |
| LR Certificate | 1SAA941002-0501 |
| RINA Certificate | RINA_ELE376813CS |
| RMRS Certificate | 1SAA941001-0701 |
| UL Certificate | E48139-19990512 |

Container Information

| | |
|--------------------------------|---------|
| Package Level 1 Units | 1 piece |
| Package Level 1 Width | 139 mm |
| Package Level 1 Height | 107 mm |
| Package Level 1 Depth / Length | 75.5 mm |

| | |
|--------------------------------|---------------|
| Package Level 1 Gross Weight | 0.857 kg |
| Package Level 1 EAN | 4013614442247 |
| Package Level 2 Units | 20 piece |
| Package Level 2 Width | 393 mm |
| Package Level 2 Height | 227 mm |
| Package Level 2 Depth / Length | 290 mm |
| Package Level 2 Gross Weight | 17.703 kg |
| Package Level 2 EAN | 4013614483387 |

Classifications

| | |
|------------------------------------|--------------------------------------|
| Object Classification Code | F |
| ETIM 4 | EC001080 - Electronic overload relay |
| ETIM 5 | EC001080 - Electronic overload relay |
| ETIM 6 | EC001080 - Electronic overload relay |
| ETIM 7 | EC001080 - Electronic overload relay |
| ETIM 8 | EC001080 - Electronic overload relay |
| eClass | V11.0 : 27371502 |
| UNSPSC | 39122330 |
| IDEA Granular Category Code (IGCC) | 5365 >> Electronic overload relay |
| E-Number (Finland) | 3706581 |
| E-Number (Sweden) | 3210246 |

Accessories

| Identifier | Description | Type | Quantity | Unit Of Measure |
|-----------------|-----------------------------|-------------|----------|-----------------|
| 1SAZ901901R1001 | DB96 Single Mounting Kit | DB96 | 1 | piece |
| 1SAX101911R1001 | DRS-F-01 Remote Reset Coil | DRS-F-01 | 1 | piece |
| 1SAX101911R1002 | DRS-F-02 Remote Reset Coil | DRS-F-02 | 1 | piece |
| 1SAX101911R1003 | DRS-F-03 Remote Reset Coil | DRS-F-03 | 1 | piece |
| 1SAX101911R1004 | DRS-F-04 Remote Reset Coil | DRS-F-04 | 1 | piece |
| 1SAX101911R1011 | DRS-F-EF-01 Remote Coil | DRS-F-EF-01 | 1 | piece |
| 1SAX101911R1012 | DRS-F-EF-02 Remote Coil | DRS-F-EF-02 | 1 | piece |
| 1SAX101911R1013 | DRS-F-EF-03 Remote Coil | DRS-F-EF-03 | 1 | piece |
| 1SAX101911R1014 | DRS-F-EF-04 Remote Coil | DRS-F-EF-04 | 1 | piece |
| 1SAZ701903R1001 | WRH-F Holder | WRH-F | 1 | piece |
| 1SAZ701903R1011 | WRB-400 Bowden Wire | WRB-400 | 1 | piece |
| 1SAZ701903R1012 | WRB-600 Bowden Wire | WRB-600 | 1 | piece |
| 1SAZ701903R1013 | WRB-1000 Bowden Wire | WRB-1000 | 1 | piece |
| 1SAZ701903R1030 | WRBG Gasket | WRBG | 1 | piece |
| 1SFA616162R1014 | KPR3-101L Reset push button | KPR-101L | 1 | piece |

Categories

Low Voltage Products and Systems → Control Products → Contactors → Electronic Overload Relays

