

Product data sheet

Specifications

SQUARE D



NEMA Motor Starter, Type S, replacement coil, 110/120VAC 50/60Hz, NEMA Size 4 starters and 8903SV lighting contactors

3109140038

Product availability: Stock - Normally stocked in distribution facility

Price*: 254.00 USD

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SF contactor Class 8903 type SV lighting contactor Class 8910 type SYD230 contactor

Complementary

NEMA size	4
[Ue] rated operational voltage	120 V AC 60 Hz 110 V AC 50 Hz
inrush power in VA	1185 VA 1260 VA
Average consumption	89 VA 85 VA
Height	2.9 in (73 mm)
Width	2.6 in (65 mm)
Depth	2.5 in (62.7 mm)

Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
GTIN	785901323563
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.70 in (6.858 cm)
Package 1 Width	4.10 in (10.414 cm)
Package 1 Length	2.40 in (6.096 cm)
Package 1 Weight	19.680 oz (557.918 g)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Contractual warranty

Warranty	18 months
----------	-----------


Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.


[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Not applicable, out of EU RoHS legal scope

Use Again

 Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No