SIEMENS

Data sheet 3RB3026-1VB0



Overload relay 10...40 A Electronic For motor protection Size S0, Class 10E Contactor mounting Main circuit: Screw Auxiliary circuit: Screw Manual-Automatic-Reset

product brand name	SIRIUS	
product designation	solid-state overload relay	
product type designation	3RB3	
General technical data		
size of overload relay	S0	
size of contactor can be combined company-specific	S0	
power loss [W] for rated value of the current at AC in hot operating state	3 W	
• per pole	1 W	
insulation voltage with degree of pollution 3 at AC rated value	690 V	
surge voltage resistance rated value	6 kV	
maximum permissible voltage for protective separation		
 in networks with ungrounded star point between auxiliary and auxiliary circuit 	300 V	
 in networks with grounded star point between auxiliary and auxiliary circuit 	300 V	
 in networks with ungrounded star point between main and auxiliary circuit 	600 V	
 in networks with grounded star point between main and auxiliary circuit 	690 V	
shock resistance	15g / 11 ms	
 according to IEC 60068-2-27 	15g / 11 ms; Signaling contact 97 / 98 in position "Tripped": 9g / 11 ms	
thermal current	40 A	
reference code according to IEC 81346-2	F	
Substance Prohibitance (Date)	10/01/2009	
SVHC substance name	Lead - 7439-92-1 Lead monoxide (lead oxide) - 1317-36-8	
Weight	0.26 kg	
Ambient conditions		
installation altitude at height above sea level maximum	2 000 m	
ambient temperature		
during operation	-25 +60 °C	
during storage	-40 +80 °C	
during transport	-40 +80 °C	
temperature compensation	-25 +60 °C	
relative humidity during operation	10 95 %	
Main circuit		
number of poles for main current circuit	3	
adjustable current response value current of the current- dependent overload release	10 40 A	
operating voltage		
• rated value	690 V	

at AC-3e rated value maximum	690 V
	50 60 Hz
operational current rated value	
operational current rated value	40 A
operational current at AC-3e at 400 V rated value	40 A
operating power	
• for 3-phase motors at 400 V at 50 Hz	5.5 18.5 kW
• for AC motors at 500 V at 50 Hz	7.5 22 kW
• for AC motors at 690 V at 50 Hz	11 37 kW
Auxiliary circuit	
design of the auxiliary switch	integrated
number of NC contacts for auxiliary contacts	1
• note	for contactor disconnection
number of NO contacts for auxiliary contacts	1
• note	for message "tripped"
number of CO contacts for auxiliary contacts	0
operational current of auxiliary contacts at AC-15	
• at 24 V	4 A
• at 110 V	4 A
• at 120 V	4 A
• at 125 V	4 A
● at 230 V	3 A
operational current of auxiliary contacts at DC-13	
• at 24 V	2 A
• at 60 V	0.55 A
● at 110 V	0.3 A
● at 125 V	0.3 A
● at 220 V	0.11 A
Protective and monitoring functions	
trip class	CLASS 10E
design of the overload release	electronic
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
• at 480 V rated value	40 A
at 480 V rated value at 600 V rated value	40 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL	
at 480 V rated value at 600 V rated value	40 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL	40 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit	40 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link	40 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit	40 A B600 / R300
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required	40 A B600 / R300 gG: 125 A, J: 150 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 45 mm 84 mm
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 45 mm 84 mm
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link a for short-circuit protection of the main circuit a with type of coordination 1 required a with type of assignment 2 required b for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection for main current circuit	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes screw-type terminals
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link a for short-circuit protection of the main circuit a with type of coordination 1 required a with type of assignment 2 required b for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection for main current circuit for auxiliary and control circuit arrangement of electrical connectors for main current	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes screw-type terminals screw-type terminals
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection for main current circuit for auxiliary and control circuit arrangement of electrical connectors for main current circuit	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes screw-type terminals screw-type terminals
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection for main current circuit for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts	gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes screw-type terminals screw-type terminals Top and bottom
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/mounting/dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection for main current circuit for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid	9G: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes screw-type terminals screw-type terminals Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²)
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection for main current circuit for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid stranded	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes screw-type terminals screw-type terminals Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²) 2x 10 mm²
at 480 V rated value at 600 V rated value contact rating of auxiliary contacts according to UL Short-circuit protection design of the fuse link for short-circuit protection of the main circuit with type of coordination 1 required with type of assignment 2 required for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection for main current circuit for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections for main contacts solid stranded solid or stranded	40 A B600 / R300 gG: 125 A, J: 150 A gG: 80 A, J: 100 A fuse gG: 6 A any Contactor mounting 87 mm 45 mm 84 mm Yes screw-type terminals screw-type terminals Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²) 2x 10 mm² 1x (1 10 mm²), 2x (1 10 mm²)

for auxiliary contacts	
— solid	1x (0.5 4 mm²), 2x (0.5 2.5 mm²)
— solid or stranded	1x (0,5 4 mm²), 2x (0,5 2,5 mm²)
 finely stranded with core end processing 	1x (0.5 2.5 mm²), 2x (0.5 1.5 mm²)
 for AWG cables for auxiliary contacts 	1x (20 14), 2x (20 14)
tightening torque	
 for main contacts with screw-type terminals 	2 2.5 N·m
 for auxiliary contacts with screw-type terminals 	0.8 1.2 N·m
design of screwdriver shaft	Diameter 5 to 6 mm
size of the screwdriver tip	Pozidriv PZ 2
design of the thread of the connection screw	
• for main contacts	M4
 of the auxiliary and control contacts 	M3
Electrical Safety	
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Communication/ Protocol	
type of voltage supply via input/output link master	No
Electromagnetic compatibility	
conducted interference	
 due to burst according to IEC 61000-4-4 	2 kV (power ports), 1 kV (signal ports) corresponds to degree of severity 3
• due to conductor-earth surge according to IEC 61000-4-5	2 kV (line to earth) corresponds to degree of severity 3
 due to conductor-conductor surge according to IEC 61000-4-5 	1 kV (line to line) corresponds to degree of severity 3
 due to high-frequency radiation according to IEC 61000- 4-6 	10 V in frequency range 0.15 to 80 MHz, modulation 80 % AM with 1 kHz
field-based interference according to IEC 61000-4-3	10 V/m
electrostatic discharge according to IEC 61000-4-2	6 kV contact discharge / 8 kV air discharge
Display	
display version for switching status	Slide switch
Approvals Certificates	

Approvals Certificates **General Product Approval**







Confirmation





For use in hazard-**Test Certificates** Marine / Shipping **EMV** ous locations



<u>KC</u>



Special Test Certific-<u>ate</u>

Type Test Certificates/Test Report



Marine / Shipping **Environment**









Confirmation

Environmental Con-firmations

Further information

Information on the packaging https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RB3026-1VB0

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RB3026-1VB0

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)


https://support.industry.siemens.com/cs/ww/en/ps/3RB3026-1VB0


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax de.aspx?mlfb=3RB3026-1VB0&lang=en


Characteristic: Tripping characteristics, I²t, Let-through current https://support.industry.siemens.com/cs/ww/en/ps/3RB3026-1VB0/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RB3026-1VB0&objecttype=14&gridview=view1







last modified: 3/11/2024 🖸