## **DATASHEET - NZMH1-4-A40**



## Circuit-breaker, 4p, 40A

Part no. NZMH1-4-A40

284422 4363459

EL Number

(Norway)



General specifications	
Product name	Eaton Moeller series NZM molded case circuit breaker thermo-magnetic
Part no.	NZMH1-4-A40
EAN	4015082844226
Product Length/Depth	84.5 millimetre
Product height	145 millimetre
Product width	120 millimetre
Product weight	1.324 kilogram
Compliances	RoHS conform
Certifications	IEC/EN 60947
Product Tradename	NZM
Product Type	Molded case circuit breaker
Product Sub Type	Thermo-magnetic
Delivery program	
Application	Use in unearthed supply systems at 690 V
Туре	Circuit breaker
	NZM1
Circuit breaker frame type  Number of poles	
·	Four-pole
Amperage Rating	40 A
Release system  Features	Thermomagnetic release  Protection unit
Special features	Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) Rated current = rated uninterrupted current: 40 A Set value in neutral conductor is synchronous with set value Ir of main pole. Terminal capacity hint: Up to 95 mm² can be connected depending on the cable manufacturer.
echnical Data - Electrical	
Voltage rating	690 V - 690 V
Rated insulation voltage (Ui)	690 V AC
Rated impulse withstand voltage (Uimp) at auxiliary contacts	6000 V
Rated impulse withstand voltage (Uimp) at auxiliary contacts  Rated impulse withstand voltage (Uimp) at main contacts	6000 V 6000 V
Rated impulse withstand voltage (Uimp) at main contacts	6000 V
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor	6000 V 200% of phase conductor
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min	6000 V 200% of phase conductor 8 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max	6000 V 200% of phase conductor 8 A 10 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Iii) - max  Overload current setting (Ir)	6000 V 200% of phase conductor 8 A 10 A 32 A - 40 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min	6000 V 200% of phase conductor 8 A 10 A 32 A - 40 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Iir) - max  Overload current setting (Irr)  Overload current setting (Irr) - min  Overload current setting (Irr) - max	6000 V 200% of phase conductor 8 A 10 A 32 A - 40 A 32 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min  Overload current setting (Ir) - max  Short delay current setting (Isd) - min	6000 V 200% of phase conductor  8 A 10 A 32 A - 40 A 32 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min  Overload current setting (Ir) - max  Short delay current setting (Isd) - min  Short delay current setting (Isd) - max	6000 V 200% of phase conductor 8 A 10 A 32 A - 40 A 32 A 40 A 0 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min  Overload current setting (Ir) - max  Short delay current setting (Isd) - min  Short delay current setting (Isd) - max  Short-circuit release non-delayed setting - min	6000 V 200% of phase conductor  8 A 10 A 32 A - 40 A 32 A 40 A 0 A 0 A 320 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min  Overload current setting (Ir) - max  Short delay current setting (Isd) - min  Short delay current setting (Isd) - max  Short-circuit release non-delayed setting - min  Short-circuit release non-delayed setting - max	6000 V 200% of phase conductor  8 A 10 A 32 A - 40 A 32 A 40 A 0 A 0 A 320 A 400 A
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min  Overload current setting (Ir) - max  Short delay current setting (Isd) - min  Short delay current setting (Isd) - max  Short-circuit release non-delayed setting - min  Short-circuit release non-delayed setting - max  Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 230 V, 50/60 Hz	6000 V 200% of phase conductor  8 A 10 A 32 A - 40 A 32 A 40 A 0 A 0 A 320 A 400 A 100 kA
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min  Overload current setting (Ir) - max  Short delay current setting (Isd) - min  Short delay current setting (Isd) - max  Short-circuit release non-delayed setting - min  Short-circuit release non-delayed setting - max  Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 230 V, 50/60 Hz	6000 V 200% of phase conductor  8 A 10 A 32 A - 40 A 32 A 40 A 0 A 0 A 320 A 400 A 100 kA 50 kA
Rated impulse withstand voltage (Uimp) at main contacts  Current rating of neutral conductor  Instantaneous current setting (Ii) - min  Instantaneous current setting (Ii) - max  Overload current setting (Ir)  Overload current setting (Ir) - min  Overload current setting (Ir) - max  Short delay current setting (Isd) - max  Short delay current setting (Isd) - max  Short-circuit release non-delayed setting - min  Short-circuit release non-delayed setting - max  Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 230 V, 50/60 Hz  Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 440 V, 50/60 Hz	6000 V 200% of phase conductor  8 A 10 A 32 A - 40 A 32 A 40 A 0 A 0 A 320 A 400 A 100 kA 50 kA 35 kA

Rated short-circuit making capacity Icm at 400/415 V, 50/60 Hz	220 kA
Rated short-circuit making capacity Icm at 440 V, 50/60 Hz	154 kA
Rated short-circuit making capacity Icm at 525 V, 50/60 Hz	40 kA
Rated short-circuit making capacity Icm at 690 V, 50/60 Hz	17 kA
Short-circuit total breaktime	< 10 ms
Electrical connection type of main circuit	Frame clamp
Isolation	500 V AC (between auxiliary contacts and main contacts) 300 V AC (between the auxiliary contacts)
Number of operations per hour - max	120
Handle type	Rocker lever
Utilization category	A (IEC/EN 60947-2)
Overvoltage category	III
Pollution degree	3
Lifespan, electrical	10000 operations at 400 V AC-1 7500 operations at 690 V AC-1 10000 operations at 415 V AC-1
Direction of incoming supply	As required
Technical Data - Mechanical	
Mounting Method	Built-in device fixed built-in technique Fixed DIN rail (top hat rail) mounting optional
Degree of protection	IP20 (basic degree of protection, in the operating controls area) IP20
Degree of protection (IP), front side	IP40 (with insulating surround) IP66 (with door coupling rotary handle)
Degree of protection (terminations)	IP00 (terminations, phase isolator and strip terminal) IP10 (tunnel terminal)
Protection against direct contact	Finger and back-of-hand proof to DIN EN 50274/VDE 0106 part 110
Shock resistance	20 g (half-sinusoidal shock 20 ms)
Number of auxiliary contacts (change-over contacts)	0
Number of auxiliary contacts (normally closed contacts)	0
Number of auxiliary contacts (normally open contacts)	0
Position of connection for main current circuit	Front side
Climatic proofing	Damp heat, cyclic, to IEC 60068-2-30 Damp heat, constant, to IEC 60068-2-78
Special features	Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity lcn) Rated current = rated uninterrupted current: 40 A Set value in neutral conductor is synchronous with set value Ir of main pole. Terminal capacity hint: Up to 95 mm² can be connected depending on the cable manufacturer.
Lifespan, mechanical	20000 operations
Technical Data - Mechanical - Terminals	
Standard terminals	Box terminal
Optional terminals	Connection on rear. Screw terminal. Tunnel terminal
Terminal capacity (control cable)	0.75 mm <sup>2</sup> - 1.5 mm <sup>2</sup> (2x) 0.75 mm <sup>2</sup> - 2.5 mm <sup>2</sup> (1x)
Terminal capacity (aluminum solid conductor/cable)	10 mm <sup>2</sup> - 16 mm <sup>2</sup> (2x) direct at switch rear-side connection 10 mm <sup>2</sup> - 16 mm <sup>2</sup> (1x) direct at switch rear-side connection 16 mm <sup>2</sup> (1x) at tunnel terminal
Terminal capacity (aluminum stranded conductor/cable)	$25~\text{mm}^2$ - $35~\text{mm}^2$ (1x) direct at switch rear-side connection $25~\text{mm}^2$ - $35~\text{mm}^2$ (2x) direct at switch rear-side connection $25~\text{mm}^2$ - $95~\text{mm}^2$ (1x) at tunnel terminal
Terminal capacity (copper busbar)	Min. 12 mm x 5 mm direct at switch rear-side connection Max. 16 mm x 5 mm direct at switch rear-side connection M6 at rear-side screw connection
Terminal capacity (copper solid conductor/cable)	10 mm <sup>2</sup> - 16 mm <sup>2</sup> (1x) direct at switch rear-side connection 6 mm <sup>2</sup> - 16 mm <sup>2</sup> (2x) direct at switch rear-side connection 6 mm <sup>2</sup> - 16 mm <sup>2</sup> (2x) at box terminal 10 mm <sup>2</sup> - 16 mm <sup>2</sup> (1x) at box terminal 16 mm <sup>2</sup> (1x) at tunnel terminal
Terminal capacity (copper stranded conductor/cable)	25 mm² (2x) direct at switch rear-side connection $6 \text{ mm²} - 25 \text{ mm²}$ (2x) at box terminal $10 \text{ mm²} - 70 \text{ mm²}$ (1x) at box terminal $25 \text{ mm²} - 95 \text{ mm²}$ (1x) at 1-hole tunnel terminal $10 \text{ mm²} - 70 \text{ mm²}$ (1x) at 1-kole tunnel terminal $10 \text{ mm²} - 70 \text{ mm²}$ (1x) direct at switch rear-side connection
Terminal capacity (copper strip)	Min. 2 segments of 9 mm x 0.8 mm at box terminal

	Max. 9 segments of 9 mm x 0.8 mm at box terminal
Design verification as per IEC/EN 61439 - technical data	
Rated operational current for specified heat dissipation (In)	40 A
Equipment heat dissipation, current-dependent	10.66 W
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	70 °C
Ambient storage temperature - min	40 °C
Ambient storage temperature - max	70 °C
Design verification as per IEC/EN 61439	
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
Additional information	
Functions	System and cable protection

## **Technical data ETIM 9.0**

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss13-27-37-04-09 [AJZ716018])

Rated permanent current lu	Α	40
Rated voltage	V	690 - 690
Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	50
Overload release current setting	А	32 - 40
Adjustment range short-term delayed short-circuit release	Α	0 - 0
Adjustment range undelayed short-circuit release	Α	8 - 10
Power loss	W	10.7
Device construction		Built-in device fixed built-in technique
Integrated earth fault protection		No
Type of electrical connection of main circuit		Frame clamp
Suitable for DIN rail (top hat rail) mounting		No
DIN rail (top hat rail) mounting optional		Yes
Number of auxiliary contacts as normally closed contact		0
Number of auxiliary contacts as normally open contact		0
Number of auxiliary contacts as change-over contact		0
With switched-off indicator		No

With integrated under voltage release	No
Number of poles	4
Position of connection for main current circuit	Front side
Type of control element	Rocker lever
Complete device with protection unit	Yes
Motor drive integrated	No
Motor drive optional	No
Degree of protection (IP)	IP20