



NEMA Motor Starter, Type S, replacement coil, 208VAC 60Hz, 2 or 3 pole, NEMA size 2 starter and 8903SP lighting

3106340944



(!) Discontinued on: Jun 30, 2023

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SD contactor Class 8903 type SP lighting contactor

Complementary

NEMA size	2
[Ue] rated operational voltage	208 V AC 60 Hz
inrush power in VA	311 VA
Average consumption	37 VA
Height	2.6 in (66.2 mm)
Width	4.0 in (101.1 mm)
Depth	2.4 in (61.7 mm)

Ordering and shipping details

Category	US10CP118061
Discount Schedule	0CP1
GTIN	785901107392
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.50 in (6.35 cm)
Package 1 Width	2.70 in (6.858 cm)
Package 1 Length	4.00 in (10.16 cm)
Package 1 Weight	12.000 oz (340.194 g)

Contractual warranty

Warranty	18 months	

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.


Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better



EU RoHS Directive

Not applicable, out of EU RoHS legal scope