SQUARE 11



NEMA Motor Starter, Type S, replacement coil, 220/240VAC 50/60Hz, NEMA Size 4 starters and 8903SV lighting contactors

3109140047

① Discontinued

! Discontinued on: Jun 30, 2023

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SF contactor Class 8903 type SV lighting contactor Class 8910 type SVD230 contactor

Complementary

•	
NEMA size	4
[Ue] rated operational voltage	240 V AC 60 Hz 220 V AC 50 Hz
inrush power in VA	1185 VA 1260 VA
Average consumption	85 VA 89 VA
Height	2.9 in (73 mm)
Width	2.6 in (65 mm)
Depth	2.5 in (62.7 mm)

Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
GTIN	785901323587
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.60 in (6.604 cm)
Package 1 Width	2.50 in (6.35 cm)
Package 1 Length	4.00 in (10.16 cm)
Package 1 Weight	19.520 oz (553.383 g)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Contractual warranty

Warranty

18 months




Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better



EU RoHS Directive

Not applicable, out of EU RoHS legal scope