

# Specifications



Photo is representative



## Eaton ED2125L

Eaton Series C complete molded case circuit breaker, F-frame, ED, Complete breaker, Fixed thermal, fixed magnetic trip type, Two-pole, 125A, 240 Vac, 125 Vdc, 65 kAIC at 240 Vac, Line and load, 50/60 Hz

### General specifications

|                      |  |
|----------------------|--|
| PRODUCT NAME         | Eaton Series C complete molded case circuit breaker  |
| CATALOG NUMBER       | ED2125L  |
| UPC                  | 786679454244   |
| PRODUCT LENGTH/DEPTH | 3.38 in  |
| PRODUCT HEIGHT       | 6 in   |
| PRODUCT WIDTH        | 2.75 in  |
| PRODUCT WEIGHT       | 2.9 lb   |
| WARRANTY             | Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first. |
| CERTIFICATIONS       | UL Listed  |

| Product specifications     |                    |
|----------------------------|--------------------|
| AMPERAGE RATING            | 125 A              |
| VOLTAGE RATING             | 240 Vac, 125 Vdc   |
| TRIP TYPE                  | T186               |
| CIRCUIT BREAKER TYPE       | ED                 |
| CIRCUIT BREAKER FRAME TYPE | Complete breaker   |
| SERIES                     | Series C           |
| TERMINALS                  | Line and load      |
| FRAME                      | F                  |
| FREQUENCY RATING           | 50/60 Hz           |
| INTERRUPT RATING           | 65 kAIC at 240 Vac |
| NUMBER OF POLES            | Two-pole           |

| Resources                     |  |
|-------------------------------|--|
|                               | <a href="#">Application of Tap Rules to Molded Case Breaker Terminals</a>            |
| APPLICATION NOTES             | <a href="#">UL listed 100%-rated molded case circuit breakers</a>                    |
|                               | <a href="#">Application of Multi-Wire Terminals for Molded Case Circuit Breakers</a> |
| BROCHURES                     | <a href="#">Current limiting Series C molded case circuit breakers product aid</a>   |
|                               | <a href="#">Power metering and monitoring with Modbus RTU product aid</a>            |
|                               | <a href="#">Circuit breaker motor operators product aid</a>                          |
|                               | <a href="#">Plug-in adapters for molded case circuit breakers product aid</a>        |
|                               | <a href="#">StrandAble terminals product aid</a>                                     |
|                               | <a href="#">Motor protection circuit breakers product aid</a>                        |
|                               | <a href="#">Multi-wire lugs product aid</a>  |
|                               | <a href="#">Breaker service centers</a>  |
| CATALOGS                      | <a href="#">Circuit Protection, Molded Case Circuit Breakers, Volume 4, Tab 2</a>    |
| MULTIMEDIA                    | <a href="#">Circuit Breakers Explained</a>   |
|                               | <a href="#">MOEM MCCB product selection guide</a>                                    |
|                               | <a href="#">Series C F-Frame molded case circuit breakers</a>                        |
| SPECIFICATIONS AND DATASHEETS | <a href="#">Series C G-Frame molded case circuit breakers time current curves</a>    |
|                               | <a href="#">Eaton Specification Sheet - ED2125L</a>                                  |
|                               | <a href="#">Series C J-Frame molded case circuit breakers time current curves</a>    |

---

**PROJECT NAME:**

**PROJECT NUMBER:**

**PREPARED BY:**

**DATE:**

---



**Eaton Corporation plc**

Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2025 Eaton. All Rights  
Reserved.

Eaton is a registered trademark.

All other trademarks are property of  
their respective owners.

Follow us on social media to get the latest  
product and support information.

