Product datasheet

Specifications





Undervoltage trip block,Easy TeSys Power,GZ1AU,220..240V AC 50 Hz

GZ1AU225

Main

| Range | Easy TeSys |
|---------------------------|-------------------|
| Product Or Component Type | Undervoltage trip |
| Device Application | Protection |

Complementary

| Range Compatibility | EasyPact EasyPact TVS GZ1E circuit-breaker | |
|------------------------------|--|--|
| [Uc] Control Circuit Voltage | 220240 V AC 50 Hz | |
| Connections - Terminals | Screw clamp terminals | |
| Height | 89 mm | |
| Width | 18 mm | |
| Depth | 66 mm | |
| Net Weight | 0.105 kg | |

Packing Units

| PCE |
|-----------|
| 1 |
| 3.500 cm |
| 8.500 cm |
| 9.000 cm |
| 113.000 g |
| S02 |
| 42 |
| 15.000 cm |
| 30.000 cm |
| 40.000 cm |
| 4.884 kg |
| P06 |
| 672 |
| 75.000 cm |
| 60.000 cm |
| 80.000 cm |
| |

Package 3 Weight

87.144 kg

Sustainability Screen Premium

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



Transparency RoHS/REACh

Well-being performance

Reach Free Of Svhc

| Toxic Heavy Metal Free | |
|----------------------------|-----|
| Mercury Free | |
| Rohs Exemption Information | Yes |

Certifications & Standards

| Reach Regulation | REACh Declaration |
|--------------------------|--|
| Eu Rohs Directive | Compliant EU RoHS Declaration |
| China Rohs Regulation | China RoHS declaration Pro-active China RoHS declaration (out of China RoHS legal scope) |
| Environmental Disclosure | Product Environmental Profile |
| Weee | The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins |
| Circularity Profile | End of Life Information |