Product datasheet

Specifications



switch disconnector, EasyPact CVS1250NA, 4 poles, 1250A, AC23A

LV512240

Main

Range of product	EasyPact CVS8001250	
Range	EasyPact	
product name	EasyPact CVS	
Device short name	CVS1250NA	
Product or component type	Switch disconnector	
Device application	Distribution	
Poles description	4P	
network type	AC	
[le] rated operational current	1250 A AC 50/60 Hz	
[Ue] rated operational voltage	690 V AC	
Breaking capacity code	NA	
Suitability for isolation	Yes conforming to EN 60947-3	
Utilisation category	AC-23A	

Complementary

Compromontary		
Network frequency	50/60 Hz	
control type	Toggle	
Mounting mode	Fixed	
Mounting support	Backplate	
Upside connection	Front	
Downside connection	Front	
[Ui] rated insulation voltage	800 V AC	
[Uimp] rated impulse withstand voltage	8 kV	
[Icw] rated short-time withstand current	15 kA during 0.1 s conforming to IEC 60947-3	
Contact position indicator	No	
Mechanical durability	20000 cycles conforming to IEC 60947-3	
Electrical durability	AC-23A: 3000 cycles 415 V AC 50/60 Hz In conforming to IEC 60947-3	
Connection pitch	68 mm	
Height	370 mm	
Width	278 mm	
Depth	143 mm	

Net weight	
------------	--

20.2 kg

Environment

Standards	IEC 60947-3	
Product certifications	IEC	
Pollution degree	3 conforming to IEC 60664-1	
Ambient air temperature for operation	-555 ℃	
Ambient air temperature for storage	-3570 °C	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	30.7 cm
Package 1 Width	39.9 cm
Package 1 Length	47.6 cm
Package 1 Weight	23.5 kg

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

```
How we assess product sustainability \geq
```

Use Better

\gtrless Materials and Substances	
Packaging made with recycled cardboard	Νο
Packaging without single use plastic	Νο

Use Again

○ Repack and remanufacture		
Take-back	Νο	