



[TAA] Mini circuit breaker, QO, 20A, 3 pole, 208Y/120VAC, 10kA, plug in, 6mA grd fault A, pigtail

QO320GFI

Product availability: Stock - Normally stocked in distribution

Price*: 791.00 USD

Main

Product	Miniature circuit-breaker	
Range	QO	
Current Rating	20 A	
Voltage Rating	208Y/120 V AC	
Mounting Type	Plug-in	
Number of Poles	3P	
Circuit Breaker Type	Ground fault protecting class A 6 mA	
Ratings	Not rated	
Electrical Connection	Pressure plate	

Complementary

Interrupt Rating	10 kA 208Y/120 V AC	
Number of Panel Spaces	3	
Wire Size	AWG 14AWG 8 copper AWG 12AWG 8 aluminium	
Tightening Torque	35.4 lbf.in (4 N.m) 40.7 lbf.in (4.6 N.m) 0.0060.03 in² (420 mm²) (AWG 12AWG 4)	
Height	4.1 in (105 mm)	
Width	2.2 in (57 mm)	
Depth	2.9 in (74 mm)	
Product Weight	1.323 lb(US) (0.600 kg)	

Environment

Certifications	UL Listed CSA
Ambient Rating	104 °F (40 °C)

Ordering and shipping details

Category	US1DE2A00103
Discount Schedule	DE2A
GTIN	785901298588
Returnability	Voc

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Country of origin IE

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.50 in (6.350 cm)
Package 1 Width	3.30 in (8.382 cm)
Package 1 Length	6.40 in (16.256 cm)
Package 1 Weight	21.952 oz (622.328 g)

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	Yes
EU RoHS Directive	Compliant with Exemptions
REACh Regulation	REACh Declaration
China RoHS Regulation	China RoHS declaration
California proposition 65	WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov

Use Again

○ Repack and remanufacture	
Take-back	No